

THREE PHASE

| NUMBER OF CELLS | DC VOLTAGE | CHARGER MODEL | 8 HR A.H RATING | MAX DC OUTPUT | AC AMP DRAW | | | | CABINET STYLE |
|--------------------|---------------|------------------|--------------------|------------------|-------------|-----|-----|-----|------------------|
| | | | | | 208 | 240 | 480 | 575 | |
| 6 | 12 | 3NE6-600 | 511-600 | 120 | 7 | 6 | 3 | 3 | L |
| 6 | 12 | 3NE6-725 | 601-725 | 145 | 9 | 8 | 4 | 3 | L |
| 6 | 12 | 3NE6-750 | 601-750 | 150 | 9 | 8 | 4 | 3 | L |
| 6 | 12 | 3NE6-900 | 751-900 | 180 | 14 | 12 | 6 | 5 | L |
| 6 | 12 | 3NE6-1050 | 901-1050 | 210 | 14 | 12 | 6 | 5 | L |
| 6 | 12 | 3NE6-1200 | 1051-1200 | 240 | 16 | 14 | 7 | 6 | L |
| 12 | 24 | 3NE12-380 | 251-380 | 76 | 10 | 8 | 4 | 3 | L |
| 12 | 24 | 3NE12-450 | 381-450 | 90 | 12 | 10 | 5 | 4 | L |
| 12 | 24 | 3NE12-510 | 451-510 | 102 | 14 | 12 | 6 | 5 | L |
| 12 | 24 | 3NE12-600 | 511-600 | 120 | 16 | 14 | 7 | 6 | L |
| 12 | 24 | 3NE12-725 | 601-725 | 145 | 18 | 16 | 8 | 7 | L |
| 12 | 24 | 3NE12-750 | 601-750 | 150 | 18 | 16 | 8 | 7 | L |
| 12 | 24 | 3NE12-900 | 751-900 | 180 | 23 | 20 | 10 | 9 | L |
| 12 | 24 | 3NE12-1050 | 901-1050 | 210 | 25 | 22 | 11 | 9 | L |
| 12 | 24 | 3NE12-1200 | 1051-1200 | 240 | 26 | 24 | 12 | 10 | L |
| 18 | 36 | 3NE18-380 | 251-380 | 76 | 16 | 14 | 7 | 6 | L |
| 18 | 36 | 3NE18-450 | 381-450 | 90 | 18 | 16 | 8 | 7 | L |
| 18 | 36 | 3NE18-510 | 451-510 | 102 | 21 | 18 | 9 | 8 | L |
| 18 | 36 | 3NE18-600 | 511-600 | 120 | 22 | 20 | 10 | 9 | L |
| 18 | 36 | 3NE18-725 | 601-725 | 145 | 27 | 24 | 12 | 10 | L |
| 18 | 36 | 3NE18-750 | 601-750 | 150 | 27 | 24 | 12 | 10 | L |
| 18 | 36 | 3NE18-900 | 751-900 | 180 | 35 | 32 | 16 | 14 | L |
| 18 | 36 | 3NE18-1050 | 901-1050 | 210 | 35 | 34 | 17 | 14 | L |
| 18 | 36 | 3NE18-1200 | 1051-1200 | 240 | 38 | 36 | 18 | 15 | L |
| 24 | 48 | 3NE24-380 | 251-380 | 76 | 22 | 20 | 10 | 9 | L |
| 24 | 48 | 3NE24-450 | 381-450 | 90 | 25 | 22 | 11 | 9 | L |
| 24 | 48 | 3NE24-510 | 451-510 | 102 | 27 | 24 | 12 | 10 | L |
| 24 | 48 | 3NE24-600 | 511-600 | 120 | 29 | 26 | 13 | 11 | L |
| 24 | 48 | 3NE24-725 | 601-725 | 145 | 33 | 30 | 15 | 13 | L |
| 24 | 48 | 3NE24-750 | 601-750 | 150 | 33 | 30 | 15 | 13 | L |
| 24 | 48 | 3NE24-900 | 751-900 | 180 | 42 | 36 | 18 | 15 | L |
| 24 | 48 | 3NE24-1050 | 901-1050 | 210 | 44 | 40 | 20 | 17 | L |
| 40 | 80 | 3NE40-350 | 350 | 70 | 44 | 42 | 21 | | L |
| 40 | 80 | 3NE40-510 | 510 | 102 | 44 | 42 | 21 | | L |
| 40 | 80 | 3NE40-625 | 625 | 125 | 46 | 44 | 22 | | L |
| 40 | 80 | 3NE40-750 | 750 | 150 | 50 | 47 | 24 | | L |

ALL CHARGERS ARE SET UP FOR 208/240/480 A.C. VOLTS
575 A.C. VOLTS SPECIAL ORDER